

FANTEC PGS-300

Power Station & Solar Generator 300W 296Wh

Manufacturer-Item-No. 2557

EAN 4250273425574



Portable Power Station

Lithium Ion Battery

Solar generator



FANTEC PGS-300

Power Station & Solar Generator 300W 296Wh

Pure, mobile, clear Power

Maximum 300W power with 296Wh capacity. Short-term 600W. Together with a solar panel (not included), the PGS-300 is a practical mobile power station and a useful solar generator for home and on the road.

Extensive charging options for USB devices

Supports charging of mobile devices via USB, or via USB QC3 fast charging technology, or via USB-C for iPad. USB-C supports PD technology.

230V AC to go

It's a normal AC 230V socket on the PGS-300, with 230V alternating voltage in inverter quality. That means: as a pure sine wave for sensitive electronic devices. For "normal" small cable tools up to 300W, battery tools for recharging batteries anyway. But also for PCs, SAT systems, small TVs.

Clearly arranged

The display shows the load, the charge status and the remaining battery life and other important information. The individual groups of plugs can be switched on and off individually.

Handy

The handy carrying handle makes it suitable for use on the move when a little more a little more power is needed. Or because it will take longer and the old power bank is no longer sufficient. Whether smartphones, iPhones, notebooks, PCs or beamers.



FANTEC PGS-300

Power Station & Solar Generator 300W 296Wh

Manufacturer-Item-No. 2557

EAN 4250273425574



Technical Data

Equipment

Outputs:

- 1x AC 230V protective contact socket
- › 1x switch 230V on/off
- › inverter quality
- › pure sine wave
- 4x USB charging sockets:
- › 1x switch USB on/off
- › 2x 5V 2.4A
- › 1x quick charge, QC3.0 technology, max. 18W
- › 1x USB-C, PD technology, max. 45W
- 4x 12V power supply:
- › 1x 12V on/off switch
- › all connections together max. 8A, 96W
- › 3x 12V power supply
- › 1x 12V plug cigarette lighter

Inputs:

- 1x 19V 3A
- › Connection of the supplied charger AC 100~240V 50~60Hz 1.5A
- › Charging time with the original charger approx. 6 hours
- Extensive protective functions:
- › Short circuit protection
- › Protection against overload
- › Protection against overheating
- › protection against overvoltage
- › Protection against overcharging
- › Protection against deep discharge
- Temperature range working: -10°C (14°F) ~ 60°C (140°F)

Features

- 300W nominal power, 296Wh capacity:
 - › 1x switch 230V on/off
 - › inverter quality
 - › pure sine wave
- robust, stable and heavy housing, with approx. 3.7kg weight
- handy, stable handle. The PGS-300 can be carried with one hand
- central on/off switch switches off the outputs centrally. The PGS-300 is switched off when the charger is connected to the charger and the charging and the charging process is shown on the is shown on the display.
- Integrated 3W LED light, dimmable dimmable in 2 steps via control button. Additional stroboscope function and emergency signal Function: "SOS" morse signal
- Clear display shows status: Battery charge status, remaining time and power consumption Charging, remaining time and power output Discharging, plug group switched on plug group, error messages, temperature information
- Targeted switching off of the individual plug groups: USB, DC 12V, AC 230V can be be switched individually
- Automatic fan. Switched off when not in use. Automatically switches on automatically when required.

Article Measurements

- 285 × 155 × 205mm (W × H × D)
- Net weight ~3,3kg per piece

Logistic Data

- **Retail Box Measurements**
200 × 275 × 295mm (W × H × D)
- **Gross weight with Retail Box**
~4,2kg per retail box
- **Packaging Unit**
4 Pieces per box
- **Dimensions packaging unit**
415 × 310 × 585mm (W × H × D)
- **Total weight box**
17,8 kg
- **Country of Origin**
China

Included accessories

- 1× FANTEC PGS-300
- Charging adapter for 230V
- Power cable for 230V charging adapter
- Cable for 12V car plug
- Manual